

## Perfect Harmony Output Parameters

### Rated Motor Voltage

2.3 kV		3.3 kV		4.16 kV		6.0 kV		6.6 kV		11 kV		13.8 kV	
Output Current	Output kVA	Output Current	Output kVA	Output Current	Output kVA	Output Current	Output kVA	Output Current	Output kVA	Output Current	Output kVA	Output Current	Output kVA
70	300	70	400	70	500	70	700	70	800	500	8000	500	10000
100	400	100	600	100	700	100	1000	100	1000	800	15000	800	18000
140	500	140	800	140	1000	140	1500	140	1500	1400	25000	1400	31000
200	800	200	1000	200	1500	200	2000	200	2000				
260	1000	260	1500	260	1750	260	2500	260	3000				
315	1250	315	1750	315	2000	315	3000	315	3500				
375	1500	375	2000	375	2500	375	4000	375	4000				
500	2000	500	2500	500	3500	500	5000	500	6500				
660	2500	660	3500	660	4500	660	7000	660	7500				
		880	5000	880	6500	880	9000	880	9500				
		1250	7000	1250	9000	1250	13000	1250	14000				
		1400	8000	1400	10000	1400	14000	1400	16000				

#### Notes

Maximum output frequency—330 Hz (with degrading). Speed-control range—1:1000 (with encoder).